

2.1 Prepare the Target

Application Manual

www.pinetek-networks.com



Table of Contents

| | |
|--|---|
| 2.1 Prepare the Target | 5 |
| <i>Enable SPI communication</i> | 5 |
| <i>GPIO</i> | 5 |

2.1 Prepare the Target

The IOL HAT can be used with the binary `iol-master-appl` that is provided in the `/bin/` folder of the GitHub. This binary has been compiled with the `aarch-linux` toolchain for 64-bit version. For other versions and targets, please follow the instructions to build:

<https://github.com/Pinetek-Networks/iol-hat/blob/main/src-master-application/README.md>

The following instructions apply to Raspberry Pi, for other targets, please check with the corresponding instructions how to enable SPI and GPIO.

Enable SPI communication

The communication between Master Application `iol-master-appl` and the IOL HAT is done over SPI, so SPI communication needs to be enabled on the host. To enable SPI for Raspberry Pi hosts, the following instructions can be used:

```
-sudo raspi-config  
-go to: Interface Options  
-go to: SPI  
-select: Enable SPI
```

If you use another target, please verify with the documentation how to enable the SPI

GPIO

The interrupt line on between host and IOL HAT is a GPIO line. To operate, **gpio** is used as library. To install **gpio**, please use the following command:

```
sudo apt install gpio
```